

Ludvík Prouza

Sampled-data controls and the bilinear transformation

*Kybernetika*, Vol. 4 (1968), No. 4, (331)--334

Persistent URL: <http://dml.cz/dmlcz/124401>

## Terms of use:

© Institute of Information Theory and Automation AS CR, 1968

Institute of Mathematics of the Academy of Sciences of the Czech Republic provides access to digitized documents strictly for personal use. Each copy of any part of this document must contain these

*Terms of use.*



This paper has been digitized, optimized for electronic delivery and stamped with digital signature within the project *DML-CZ: The Czech Digital Mathematics Library*  
<http://project.dml.cz>

# Sampled-Data Controls and the Bilinear Transformation

LUDVÍK PROUZA

By the use of the bilinear transformation, the methods devised for the study of continuous control systems may be applied to sampled-data systems. A simple method facilitating considerably the practical performing of the transformation is presented here.

## 1. INTRODUCTION

Recently, two methods facilitating the substitution

$$(1) \quad z = \frac{s+1}{s-1}$$

in the polynomial

$$(2) \quad F(z) = a_n z^n + a_{n-1} z^{n-1} + \dots + a_1 z + a_0$$

have been published in [1], [2]. However, special coefficients for each degree of (2) must be computed in advance in the method described in [1], special (although simple) matrices are needed in the method of [2]. In this article, a very simple method without these inconveniences will be derived.

## 2. PERFORMING THE BILINEAR TRANSFORMATION

We will make the substitution (1) in two stages

$$(3) \quad z - 1 = \frac{2}{w},$$

$$(4) \quad w + 1 = s.$$

332 First of all, the coefficients  $b_k$  ( $k = 0, 1, \dots, n$ ) in the equation

$$(5) \quad F(z) = b_n(z-1)^n + \dots + b_1(z-1) + b_0$$

are needed. By successive differentiation on both sides of (5), one gets

$$(6) \quad b_k = F^{(k)}(1)/k!.$$

Then, we substitute from (3) in (5). One gets

$$(7) \quad F(z) = \frac{1}{w^n} \cdot (b_0 w^n + 2b_1 w^{n-1} + \dots + 2^n b_n) = G(w)/w^n.$$

Then, we substitute from (4) in  $G(w)$ .

$$(8) \quad G(w) = c_n s^n + c_{n-1} s^{n-1} + \dots + c_1 s + c_0.$$

By successive differentiation on both sides of (8), one gets

$$(9) \quad c_k = G^{(k)}(-1)/k!.$$

Finally, one gets

$$(10) \quad F(z) = \frac{1}{(s-1)^n} \cdot (c_n s^n + \dots + c_1 s + c_0).$$

The coefficients in (6) and (9) are easily computed by the known method of Horner schemes.

Thus, the whole procedure can be summarized as follows:

1. Find the coefficients in (6) by the first sequence of Horner schemes.
2. Form the coefficients of  $G(w)$  in (7).
3. Find the coefficients in (9) by the second sequence of Horner schemes.

### 3. ILLUSTRATIVE EXAMPLE

Let (as in [2])

$$F(z) = z^5 + 3z^4 + 4z^3 + 5z^2 + 2z + 4,$$

The steps 1. and 2. of the procedure are

	1	3	4	5	2	4		
		1	4	8	13	15		
1	1	4	8	13	15	19	. 1	19
		1	5	13	26			
1	1	5	13	26	41		. 2	82
		1	6	19				
1	1	6	19	45			. 4	180
		1	7					
1	1	7	26				. 8	208
		1						
1	1	8					.16	128
		1						
		1					.32	32

The step 3. of the procedure is

		19	82	180	208	128	32	
			-19	-63	-117	-91	-37	
-1	19	63	117	91	37	-5		
		-19	-44	-73	-18			
-1	19	44	73	18	19			
		-19	-25	-48				
-1	19	25	48	-30				
		-19	-6					
-1	19	6	42					
		-19						
-1	19	-13						
		19						

Thus

$$F(z) = \frac{1}{(s-1)^5} \cdot (19s^5 - 13s^4 + 42s^3 - 30s^2 + 19s - 5).$$

(The last two coefficients are incorrect in [2]. Moreover the term  $f_{3,7} = 80$  of the matrix  $F_1$  in [2] and all terms depending theorem are also incorrect. This term should be 60.)

Comparing the described method with the method of [1] (which is less laborious than that of [2]) one sees in the preceding example that 30 additions or subtractions and 6 multiplications are needed here, whereas 30 additions or subtractions and 12 multiplications are needed in [1].

Since no special expressions must be prepared in advance to perform the computations, the described method seems to be useful.

(Received January 18th, 1968.)

#### REFERENCES

- [1] Soliman J. I. - Al-Shaikh A.: Sampled-data controls and the bilinear transformation. *Automatica* 2 (1965), 235–242.
- [2] Power H. M.: The mechanics of the bilinear transformation. *IEEE Trans. E-10* (1967), 2, 114–116.

---

#### VÝTAH

### Impulsní regulace a bilineární transformace

LUDVÍK PROUZA

S pomocí bilineární transformace může být k vyšetřování impulsních regulací použito metod, navržených pro regulace spojité. V článku se navrhuje jednoduchá metoda, která podstatně usnadňuje praktické provedení transformace.

*Dr. Ludvík Prouza, CSc., Ústav pro výzkum radiotechniky, Opocínek, p. Lány na Dálku.*